

COMPRESSOR QUICK SELECT GUIDE

WHOLESALE DISTRIBUTION
NORTH AMERICA



COMPRESSOR MODEL NOMENCLATURE



AE	4	440	Y	AA	1A
AEA	4	440	Y	XA	
COMPRESSOR FAMILY (FIRST TWO DIGITS)	APPLICATION	FIRST DIGIT IS THE NUMBER OF DIGITS IN BTU/H CAPACITY	REFRIGERANT	VOLTAGE	RELEASE VARIANT
RELEASE VARIANT (THE THIRD DIGIT)		LAST TWO DIGITS ARE THE FIRST TWO DIGITS IN RATED BTU/H CAPACITY			

- AE
- AG
- AH
- AJ
- AK
- AN
- AV
- AW
- AZ
- RG
- RK
- SA
- SF
- TA
- TC
- TP
- HG
- TH
- VS

- A = 1st
- B = 2nd
- C = 3rd
- etc...

In this example (4) total digits, with the first two (40), or 4,000 BTU capacity

Primary Application Parameters		
Evap Temperature	Rating Point	Motor Starting Torque
1. Low	-10°F	Normal
2. Low	-10°F	High
3. High	+45°F	Normal
4. High	+45°F	High
5. A/C & H/P	+45°F	Normal
6. Medium	+20°F	Normal
7. Medium	+20°F	High
8. Air Cond	+49°F	Normal
9. Commercial	+20°F	High
0. Commercial	+20°F	Normal
F. Low – Vapor Inj	-10°F	High
G. Low – Liquid Inj	-10°F	High
W. L/MBP	-10°F / +20°F	Normal
X. L/MBP	-10°F / +20°F	High

Primary Refrigerants [†]
A = R12
B = R410A
C = R407C
E = R22
U = R290
W = R22/R407C
X = (CBP Models Only) R404A, R507, R134a, R22, R407A, R407F
Y = R134a
Z = R404A/R507

[†]Refrigerant by item numbers as shown.

Voltage Codes
AA = 115/60/1
AB = 115/60/1; 90/50/1
CZ = 230/60/1; 208/50/1
DS = 115-127/60/1
FA = 208-230/60/3
FZ = 220-240/50/1
KZ = 220/60/3; 220/50/3
NA = 208-230/60/1
TZ = 440/60/3; 400/50/3
VA = 265/60/1; 220-240/50/1
XA = 115/60/1; 100/50/1
XB = 230/60/1; 200/50/1
XC = 220-240/50/1
XD = 208-230/60/1; 200/50/1
XF = 208-230/60/3; 200-240/50/3
XG = 460/60/3; 380-420/50/3
XH = 575/60/3; 480-520/50/3
XN = 208-230/60/1; 200-220/50/1
XP = 220/60/1; 200/50/1
XT = 200-230/60/3; 200-220/50/3
XU = 100/60/1; 100/50/1
XV = 265/60/1

NOTE: For explanation of compressor families and codes, contact Tecumseh Products Company.

Compressor Replacement Guides and Quick Selects

This document is NOT to be used as a drop-in replacement guide. The cross-reference is offered as a tool to help identify potential replacement options based on performance. Mounting and tubing connections are likely to differ from the original compressor. With use, system performance will most likely have changed from initial specifications. Careful review of current application requirements is essential. **IT IS THE RESPONSIBILITY OF THE SERVICE PERSON TO ASSURE THEY HAVE PURCHASED A REPLACEMENT PRODUCT WHICH MEETS THE NEED OF THE APPLICATION.** Failure to do so may result in misapplication requiring immediate or subsequent additional compressor replacement(s).

COMPRESSOR QUICK SELECT GUIDE

COMMERCIAL TEMPERATURE RATED @ 20°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
Commercial Temperature Rated @ 20°F														
Recip	AZA0370YXA	AZ430CR-235-J7JP	700	1/4	3/16	—	—	—	—	—	Low	1/10	R-134a	115V ~ 60Hz
Recip	THA0370YXA	TH730AR-339-J7HV	700	5/16	1/4	—	—	—	—	—	Low	1/10	R-134a	115V ~ 60Hz
Recip	AZA0395YXA	AZ440CR-236-J7JP	950	5/16	3/16	—	—	—	—	—	Low	1/9	R-134a	115V ~ 60Hz
Recip	THA0410YXA	TH750AR-340-J7HV	1050	5/16	1/4	—	—	—	—	—	Low	1/8	R-134a	115V ~ 60Hz
Recip	AKA9427ZXA	AK174AT-037-J7	2700	3/8	1/4	AKA9427ZXA	AK174AR-B37-J7	2700	3/8	1/4	High	1/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9427ZXA	AK174AT-038-J7	2700	1/2 FLARE	1/4	AKA9427ZXA	AK174AR-A38-J7	2700	1/2 FLARE	1/4	High	1/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9427ZXD	AK174ET-037-J7	2700	3/8	1/4	AKA9427ZXD	AK174ER-B37-J7	2700	3/8	1/4	High	1/4	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9427ZXD	AK174ET-038-J7	2700	3/4 Rotolock	1/4	AKA9427ZXD	AK174ER-B38-J7	2700	3/4 Rotolock	1/4	High	1/4	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9428EXA	AK164AT-038-J7	2800	3/4 Rotolock	1/4	AKA9428EXA	AK164AR-B38-J7	2800	3/4 Rotolock	1/4	High	1/3	R-22/R-407C	115V ~ 60Hz
Recip	AKA9428EXD	AK164ET-038-J7	2800	3/4 Rotolock	1/4	AKA9428EXD	AK164ER-B38-J7	2800	3/4 Rotolock	1/4	High	1/3	R-22/R-407C	208-230V ~ 60Hz
Rotary	HGA9430YXA	HG361CR-203-J7	3000	3/8	5/16	—	—	—	—	—	High	1/3	R-134a/R-513A	115V ~ 60Hz
Recip	AKA9434AXA	AK159AT-038-J7	3350	3/4 Rotolock	1/4	AKA9434AXA	AK159AR-B38-J7	3350	3/4 Rotolock	1/4	High	1/2	R-12	115V ~ 60Hz
Recip	AKA9438ZXA	AK175AT-035-J7	3750	3/8	1/4	AKA9438ZXA	AK175AR-A35-J7	3750	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9438ZXA	AK175AT-037-J7	3750	3/8	1/4	AKA9438ZXA	AK175AR-B37-J7	3750	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9438ZXA	AK175AT-038-J7	3750	3/4 Rotolock	1/4	AKA9438ZXA	AK175AR-B38-J7	3750	3/4 Rotolock	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9438ZXD	AK175ET-037-J7	3750	3/8	1/4	AKA9438ZXD	AK175ER-B37-J7	3750	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9438ZXD	AK175ET-038-J7	3750	3/4 Rotolock	1/4	AKA9438ZXD	AK175ER-B38-J7	3750	3/4 Rotolock	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9441AXA	AK163AT-038-J7	4100	3/4 Rotolock	1/4	AKA9441AXA	AK163AR-B38-J7	4100	3/4 Rotolock	1/4	High	1/2	R-12	115V ~ 60Hz
Recip	AKA9442EXA	AK165AT-038-J7	4200	3/4 Rotolock	1/4	AKA9442EXA	AK165AR-B38-J7	4200	3/4 Rotolock	1/4	High	1/2	R-22/R-407C	115V ~ 60Hz
Recip	AKA9442EXD	AK165ET-038-J7	4200	3/4 Rotolock	1/4	AKA9442EXD	AK165ER-B38-J7	4200	3/4 Rotolock	1/4	High	1/2	R-22/R-407C	208-230V ~ 60Hz
Recip	AKA9451ZXA	AK170AT-037-J7	5150	3/8	1/4	AKA9451ZXA	AK170AR-B37-J7	5150	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9451ZXA	AK170AT-038-J7	5150	3/4 Rotolock	1/4	AKA9451ZXA	AK170AR-B38-J7	5150	3/4 Rotolock	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9455ZXA	AK171AT-032-J7	5450	3/8	1/4	AKA9455ZXA	AK171AR-A32-J7	5450	3/8	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9455ZXA	AK171AT-038-J7	5450	3/4 Rotolock	1/4	AKA9455ZXA	AK171AR-B38-J7	5450	3/4 Rotolock	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9455ZXA	AK171BT-039-J7	5450	3/8	1/4	AKA9455ZXA	AK171AR-A39-J7	5450	3/8	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9455ZXD	AK171ET-037-J7	5450	3/8	1/4	AKA9455ZXD	AK171ER-B37-J7	5450	3/8	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9455ZXD	AK171ET-038-J7	5450	3/4 Rotolock	1/4	AKA9455ZXD	AK171ER-B38-J7	5450	3/4 Rotolock	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9455EXD	AK167ET-037-J7	5500	3/8	1/4	AKA9455EXD	AK167ER-B37-J7	5500	3/8	1/4	High	3/4	R-22/R-407C	208-230V ~ 60Hz
Recip	AKA9455EXD	AK167ET-038-J7	5500	3/4 Rotolock	1/4	AKA9455EXD	AK167ER-B38-J7	5500	3/4 Rotolock	1/4	High	3/4	R-22/R-407C	208-230V ~ 60Hz
Recip	AKA9462EXD	AK166ET-037-J7	6200	3/8	1/4	AKA9462EXD	AK166ER-B37-J7	6200	3/8	1/4	High	3/4	R-22/R-407C	208-230V ~ 60Hz

COMPRESSOR QUICK SELECT GUIDE

COMMERCIAL TEMPERATURE RATED @ 20°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
Commercial Temperature Rated @ 20°F														
Recip	AKA9462EXD	AK166ET-038-J7	6200	3/4 Rotolock	1/4	AKA9462EXD	AK166ER-B38-J7	6200	3/4 Rotolock	1/4	High	3/4	R-22/R-407C	208-230V ~ 60Hz
Recip	AKA9462ZXA	AK172AT-037-J7	6250	3/8	1/4	AKA9462ZXA	AK172AR-B37-J7	6250	3/8	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9462ZXA	AK172AT-038-J7	6250	3/4 Rotolock	1/4	AKA9462ZXA	AK172AR-B38-J7	6250	3/4 Rotolock	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA9462ZXD	AK172ET-037-J7	6250	3/8	1/4	AKA9462ZXD	AK172ER-B37-J7	6250	3/8	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AKA9462ZXD	AK172ET-038-J7	6250	3/4 Rotolock	1/4	AKA9462ZXD	AK172ER-B38-J7	6250	3/4 Rotolock	1/4	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip*	AWA9480ZNX	AW619ET-172-J7	7800	1/2	3/8	AWA9480ZNX	AW619EH-172-J7	7800	1/2	3/8	High	1	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip*	AWA9480ZFA	AW619RT-174-J7	8200	5/8	3/8	AWA9480ZFA	AW619RH-174-J7	8200	5/8	3/8	Low	1	R-404A/R-448A/ R-449A/R-452A	208-230V 3~ 60Hz
Recip	AJA9484EXD	AJ801ET-418-J7	8400	1/2	5/16	AJ9484E-XD3A	AJ4EM1DF646J70	8551	1/2	3/8	High	1	R-22/R-407C	208-230V ~ 60Hz
Recip	AJA9484EXD	AJ801ET-431-J7	8400	3/4 Rotolock	5/16	AJ9484E-XD3A	AJ4EM1DF646J70	8551	1/2	3/8	High	1	R-22/R-407C	208-230V ~ 60Hz
Recip	AJA9484EXD	AJ801ET-446-J7	8400	3/8	5/16	AJ9484E-XD3A	AJ4EM1DF646J70	8551	1/2	3/8	High	1	R-22/R-407C	208-230V ~ 60Hz
Recip*	AWA9490ZXT	AW616RT-174-J7	9000	5/8	3/8	AWA9490ZXT	AW616RH-174-J7	9000	5/8	3/8	High	1	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Recip	AWA9512ZXT	AW611ST-120-J7	11300	5/8	3/8	AWA9512ZXT	AW611SH-120-J7	11300	5/8	3/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Recip*	AWA9512ZXT	AW611ST-174-J7	11300	5/8	3/8	AWA9512ZXT	AW611SH-174-J7	11300	5/8	3/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Recip	AWA9512ZNX	AW611FT-099-J7	11600	5/8	3/8	AWA9512ZNX	AW611FH-099-J7	11600	5/8	3/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip*	AWA9512ZNX	AW611FT-172-J7	11600	5/8	3/8	AWA9512ZNX	AW611FH-172-J7	11600	5/8	3/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VSC9515XMA	VS320RT-109-J7	14499	3/4	1/2	—	—	—	—	—	High	2	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz
Scroll*	VSC9515XNA	VS320ET-109-J7	14622	3/4	1/2	—	—	—	—	—	High	2	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V ~ 60Hz
Scroll*	VSC9519XMA	VS321RT-109-J7	19461	3/4	1/2	—	—	—	—	—	High	3	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz
Scroll*	VSC9519XNA	VS321ET-109-J7	19501	3/4	1/2	—	—	—	—	—	High	3	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V ~ 60Hz
Scroll*	VSC9521XNA	VS322ET-109-J7	20690	3/4	1/2	—	—	—	—	—	High	3	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V ~ 60Hz
Scroll*	VSC9521XMA	VS322RT-109-J7	20843	3/4	1/2	—	—	—	—	—	High	3	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz
Scroll*	VSC9526XMA	VS323RT-109-J7	25808	3/4	1/2	—	—	—	—	—	High	4	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz
Scroll*	VSC9526XNA	VS323ET-109-J7	26033	3/4	1/2	—	—	—	—	—	High	4	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V ~ 60Hz
Scroll*	VSC9530XMA	VS324RT-110-J7	30324	3/4	1/2	—	—	—	—	—	High	4	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz
Scroll*	VSC9530XNA	VS324ET-110-J7	30328	3/4	1/2	—	—	—	—	—	High	4	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V ~ 60Hz
Recip	AGA9534ZXT	AG144ST-001-J7	33000	7/8	1/2	AGB4568ZKZ	AG144SF-105-J7	34484	7/8	1/2	High	4	R-404A/R-407A/R-448A/ R-449A/R-452A	208-230V 3~ 60Hz
Scroll*	VSC9538XNA	VS325ET-110-J7	35870	3/4	1/2	—	—	—	—	—	High	5	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V ~ 60Hz
Scroll*	VSC9538XMA	VS325RT-110-J7	36497	3/4	1/2	—	—	—	—	—	High	5	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz
Scroll*	VSC9545XMA	VS326RT-110-J7	44144	3/4	1/2	—	—	—	—	—	High	6	R-404A/R-507A/R-448A/ R-449A/R-452A/R134a/R22	208-230V 3~ 60Hz

*Replacement compressor used on Tecumseh ARGUS Condensing Unit

COMPRESSOR QUICK SELECT GUIDE

HIGH TEMPERATURE RATED @ 45°F
& HIGH TEMPERATURE AND A/C RATED @ 45°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
High Temperature Rated @ 45°F														
Recip*	AE4450Z-XN3C	AE1905E-677-J7	5900	3/8	1/4	—	—	—	—	—	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AJA4461AXA	AJ311AT-126-J7	6100	3/8	1/4	AJ4461A-XA1A	AJ4AB1AF640J70	6966	3/8	1/4	High	1/2	R-12	115V ~ 60Hz
Recip	AJA4461AXA	AJ311AT-141-J7	6100	3/4 Rotolock	5/16	AJ4461A-XA1A	AJ4AB1AF640J70	6966	3/8	1/4	High	1/2	R-12	115V ~ 60Hz
Recip	AKA4460YXA	AK168AT-032-J7	6300	3/8	1/4	AKA4460YXA	AK168AR-A32-J7	6300	3/8	1/4	High	1/2	R-134a/R-513A	115V ~ 60Hz
Recip	AKA4460YXA	AK168AT-037-J7	6300	3/8	1/4	AKA4460YXA	AK168AR-B37-J7	6300	3/8	1/4	High	1/2	R-134a/R-513A	115V ~ 60Hz
Recip	AKA4460YXA	AK168AT-038-J7	6300	3/4 Rotolock	1/4	AKA4460YXA	AK168AR-B38-J7	6300	3/4 Rotolock	1/4	High	1/2	R-134a/R-513A	115V ~ 60Hz
Recip	AKA4460YXD	AK168ET-037-J7	6300	3/8	1/4	AKA4460YXD	AK168ER-B37-J7	6300	3/8	1/4	High	3/4	R-134a	208-230V ~ 60Hz
Recip	AKA4460YXD	AK168ET-038-J7	6300	1/2 FLARE	1/4	AKA4460YXD	AK168ER-A38-J7	6300	1/2 FLARE	1/4	High	3/4	R-134a	208-230V ~ 60Hz
Recip	AKA4476YXA	AK169AT-037-J7	7680	3/8	1/4	AKA4476YXA	AK169AR-B37-J7	7680	3/8	1/4	High	3/4	R-134a/R-513A	115V ~ 60Hz
Recip	AKA4476YXA	AK169AT-038-J7	7680	3/4 Rotolock	1/4	AKA4476YXA	AK169AR-B38-J7	7680	3/4 Rotolock	1/4	High	3/4	R-134a/R-513A	115V ~ 60Hz
Recip	AKA4476YXD	AK169ET-037-J7	7680	3/8	1/4	AKA4476YXD	AK169ER-B37-J7	7680	3/8	1/4	High	3/4	R-134a/R-513A	208-230V ~ 60Hz
Recip	AKA4476YXD	AK169ET-038-J7	7680	1/2 FLARE	1/4	AKA4476YXD	AK169ER-A38-J7	7680	1/2 FLARE	1/4	High	3/4	R-134a/R-513A	208-230V ~ 60Hz
Recip	AJA4492YXA	AJ150AT-193-J7	8800	1 Rotolock	5/16	AJ4492Y-XA1A	AJ4YL1AF643J70	9739	1/2	5/16	High	3/4	R-134a/R-513A	115V ~ 60Hz
Recip	AJA4492YXA	AJ150AT-434-J7	8800	3/8	1/4	AJ4492Y-XA1A	AJ4YL1AF643J70	9739	1/2	5/16	High	3/4	R-134a/R-513A	115V ~ 60Hz
Recip	AJA4492YXD	AJ150GT-193-J7	9000	1 Rotolock	5/16	AJ4492Y-XD1A	AJ4YL1DF643J70	9602	1/2	5/16	High	3/4	R-134a	208-230V ~ 60Hz
Recip	AJA4492YXD	AJ150GT-434-J7	9000	3/8	1/4	AJ4492Y-XD1A	AJ4YL1DF643J70	9602	1/2	5/16	High	3/4	R-134a	208-230V ~ 60Hz
Recip	AJA4492AXA	AJ100AT-193-J7	9150	1 Rotolock	5/16	AJ4492A-XA1A	AJ4AL1AF643J70	10143	1/2	5/16	High	3/4	R-12	115V ~ 60Hz
Recip	AJA4492AXD	AJ100GT-193-J7	9150	1 Rotolock	5/16	AJ4492A-XD1A	AJ4AL1DF643J70	9150	1/2	5/16	High	3/4	R-12	208-230V ~ 60Hz
Recip	AJA4512YXD	AJ137ET-193-J7	12100	1 Rotolock	5/16	AJ4512Y-XD3A	AJ4YR1DF643J70	12001	1/2	5/16	High	1	R-134a/R-513A	208-230V ~ 60Hz
Recip	AJA4512AXD	AJ131GT-193-J7	12300	1 Rotolock	5/16	AJ4512A-XD3A	AJ4AR1DF643J70	13055	1/2	5/16	High	1	R-12	208-230V ~ 60Hz
Recip	AWG4520EXN	AW703FT-111-J7	20500	1-1/4 Rotolock	3/8	AWG4520EXN	AW703FH-111-J7	20500	1-1/4 Rotolock	3/8	High	1-1/2	R-22/R-407C	208-230V ~ 60Hz
Recip	AWG4524EXN	AW705FT-099-J7	24200	5/8	3/8	AWG5524EXN	AW705EH-099-J7	24200	5/8	3/8	High	2	R-22/R-407C	208-230V ~ 60Hz
High Temperature and A/C Rated @ 45°F														
Rotary	RGAS460EXA	RG121AR-001-J7LN	6000	3/8	5/16	—	—	—	—	—	Low	1/2	R-22	115V ~ 60Hz
Rotary	RK5480E-AA3A	RK5EJ1AC160J70	8000	3/8	5/16	—	—	—	—	—	Low	3/4	R-22	115V ~ 60Hz
Rotary	RK5480E-NA3A	RK5EJ1DC280J70	8000	3/8	5/16	—	—	—	—	—	Low	3/4	R-22	208-230V ~ 60Hz
Rotary	RGAS480EXA	RG151AR-003-J7LN	8100	3/8	5/16	—	—	—	—	—	Low	3/4	R-22	115V ~ 60Hz
Recip	AKA5483EXD	AK130ET-004-J7	8300	3/8	1/4	AKA5483EXD	AK130ER-004-J7	8300	3/8	1/4	Low	3/4	R-22/R-407C	208-230V ~ 60Hz
Rotary	RGAS492EXV	RG171JB-676-J7	9200	1/2	5/16	—	—	—	—	—	Low	3/4	R-22	265V ~ 60Hz
Rotary	RK5490E-AA3A	RK5EE1AC180J70	9350	1/2	5/16	—	—	—	—	—	Low	3/4	R-22	115V ~ 60Hz

*Replacement compressor used on Tecumseh ARGUS Condensing Unit

COMPRESSOR QUICK SELECT GUIDE

HIGH TEMPERATURE AND A/C RATED @ 45°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
High Temperature and A/C Rated @ 45°F														
Rotary	RK5490E-NA3A	RK5EE1DC190J70	9400	1/2	5/16	—	—	—	—	—	Low	3/4	R-22	208-230V ~ 60Hz
Recip	AKA5510EXA	AK100AT-004-J7	10000	3/8	1/4	AKA5510EXA	AK100AR-004-J7	10000	3/8	1/4	Low	3/4	R-22/R-407C	115V ~ 60Hz
Recip	AKA5510EXD	AK100ET-004-J7	10000	3/8	1/4	AKA5510EXD	AK100ER-004-J7	10000	3/8	1/4	Low	3/4	R-22/R-407C	208-230V ~ 60Hz
Recip	AKA5510EXV	AK100JB-004-J7	10000	3/8	1/4	AKA5510EXV	AK100JR-004-J7	10000	3/8	1/4	Low	3/4	R-22/R-407C	265V ~ 60Hz
Rotary	RK5510E-AA3A	RK5ES1AC200J70	10100	1/2	5/16	—	—	—	—	—	Low	3/4	R-22	115V ~ 60Hz
Rotary	RK5510E-NA3A	RK5ES1DC210J70	10260	1/2	5/16	—	—	—	—	—	Low	3/4	R-22	208-230V ~ 60Hz
Rotary	RG5510EXA	RG181AR-006-J7LN	10300	1/2	5/16	—	—	—	—	—	Low	3/4	R-22	115V ~ 60Hz
Rotary	HGA5512EXD	HG191ER-105-J7	11500	1/2	5/16	—	—	—	—	—	Low	1	R-22	208-230V ~ 60Hz
Rotary	RG5512EXV	RG191JB-007-J7	11500	1/2	5/16	—	—	—	—	—	Low	1	R-22	265V ~ 60Hz
Rotary	RK5512Y-AA3A	RK5YT1AC290J70	11854	1/2	3/8	—	—	—	—	—	Low	1	R-134a	115V ~ 60Hz
Recip	AKA5512EXA	AK111AT-004-J7	12000	3/8	1/4	AKA5512EXA	AK111AR-004-J7	12000	3/8	1/4	Low	1	R-22/R-407C	115V ~ 60Hz
Rotary	RK5512Y-NA3A	RK5YT1DC290J70	12000	1/2	3/8	—	—	—	—	—	Low	1	R-134a	208-230V ~ 60Hz
Recip	AKA5512EXD	AK111ET-004-J7	12000	3/8	1/4	AKA5512EXD	AK111ER-004-J7	12000	3/8	1/4	Low	1	R-22/R-407C	208-230V ~ 60Hz
Recip	AKA5512EXV	AK111JB-004-J7	12000	3/8	1/4	AKA5512EXV	AK111JR-004-J7	12000	3/8	1/4	Low	1	R-22/R-407C	265V ~ 60Hz
Rotary	RK5513E-AA3A	RK5EL1AC220J70	12650	1/2	5/16	—	—	—	—	—	Low	1	R-22	115V ~ 60Hz
Rotary	RK5513E-NA3A	RK5EM1DC230J70	12650	1/2	5/16	—	—	—	—	—	Low	1	R-22	208-230V ~ 60Hz
Rotary	RK5514E-AA3A	RK5EN1AC130J70	13400	1/2	5/16	—	—	—	—	—	Low	1	R-22	115V ~ 60Hz
Rotary	RK5514E-NA3A	RK5EN1DC260J70	13400	1/2	5/16	—	—	—	—	—	Low	1	R-22	208-230V ~ 60Hz
Rotary	RK5515B-NA3A	RK5BG1DC130J70	14850	1/2	5/16	—	—	—	—	—	Low	1-1/4	R-410A	208-230V ~ 60Hz
Rotary	RK5516E-NA3A	RK5EP1DC250J70	15800	1/2	3/8	—	—	—	—	—	Low	1-1/4	R-22	208-230V ~ 60Hz
Rotary	RK5519E-NA3A	RK5ER1DC270J70	18700	1/2	3/8	—	—	—	—	—	Low	1-1/2	R-22	208-230V ~ 60Hz
Recip	AWG5519EXN	AW702ET-093-J7	18800	3/4	3/8	AWG5519EXN	AW702EH-093-J7	18800	3/4	3/8	Low	1-1/2	R-22/R-407C	208-230V ~ 60Hz
Recip	AJA5519EXD	AJ220FT-206-J7	19300	1/2	5/16	AJ5519E-XD3A	AJ5ER1DF643J70	19300	1/2	5/16	Low	1-1/2	R-22/R-407C	208-230V ~ 60Hz
Recip	AWF5522EXN	AW504ET-089-J7	22400	3/4	3/8	AWG5524EXN	AW705EH-093-J7	24200	3/4	3/8	Low	1-3/4	R-22/R-407C	208-230V ~ 60Hz
Recip	AWG5524EXN	AW705ET-093-J7	24200	3/4	3/8	AWG5524EXN	AW705EH-093-J7	24200	3/4	3/8	Low	2	R-22/R-407C	208-230V ~ 60Hz
Recip	AWG5524EXN	AW705ET-099-J7	24200	5/8	3/8	AWG5524EXN	AW705EH-099-J7	24200	5/8	3/8	Low	2	R-22/R-407C	208-230V ~ 60Hz
Recip	AWG5528EXN	AW706ET-093-J7	28000	3/4	3/8	AWG5528EXN	AW706EH-093-J7	28000	3/4	3/8	Low	2-1/2	R-22/R-407C	208-230V ~ 60Hz
Recip	AWG5530EXN	AW707ET-093-J7	30200	3/4	3/8	AWG5530EXN	AW707EH-093-J7	30200	3/4	3/8	Low	2-1/2	R-22/R-407C	208-230V ~ 60Hz
Recip	AGA5553EXT	AG122RT-003-J7	54000	7/8	1/2	AGB5553EKZ	AG122RF-104-J7	52014	7/8	1/2	Low	4-1/2	R-22/R-407C	208-230V 3~ 60Hz
Recip	AGA5553EXN	AG122ET-003-J7	54000	7/8	1/2	AGB5553ECZ	AG122EF-104-J7	52014	7/8	1/2	Low	4-1/2	R-22/R-407C	208-230V ~ 60Hz

COMPRESSOR QUICK SELECT GUIDE

HIGH TEMPERATURE AND A/C RATED @ 45°F
& HIGH/COMMERCIAL TEMPERATURE RATED @ 45°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
High Temperature and A/C Rated @ 45°F														
Recip	AGC5553EXG	AG122UT-003-J7	54000	7/8	1/2	AGB5553ETZ	AG122UF-104-J7	52014	7/8	1/2	Low	4-1/2	R-22/R-407C	460V 3~ 60Hz
Recip	AGA5561EXT	AG133RT-003-J7	61000	7/8	1/2	AGB5561EKZ	AG133RF-104-J7	59848	7/8	1/2	Low	5	R-22/R-407C	208-230V 3~ 60Hz
Recip	AGA5561EXN	AG133ET-001-J7	61000	7/8	1/2	AGB5561ECZ	AG133EF-105-J7	59848	7/8	1/2	Low	5	R-22/R-407C	208-230V ~ 60Hz
Recip	AGC5561EXG	AG133UT-003-J7	61000	7/8	1/2	AGB5561ETZ	AG133UF-104-J7	59848	7/8	1/2	Low	5	R-22/R-407C	460V 3~ 60Hz
Recip	AGA5568EXT	AG144RT-001-J7	68000	7/8	1/2	AGB5568EKZ	AG144RF-105-J7	67054	7/8	1/2	Low	5-1/2	R-22/R-407C	208-230V 3~ 60Hz
Recip	AGC5568EXG	AG144UT-001-J7	68000	7/8	1/2	AGB5568ETZ	AG144UF-105-J7	67054	7/8	1/2	Low	5-1/2	R-22/R-407C	460V 3~ 60Hz
Recip	AGA5573EXG	AG188UT-001-J7	72500	7/8	1/2	AGB5573ETZ	AG188UF-105-J7	71678	7/8	1/2	Low	6	R-22/R-407C	460V 3~ 60Hz
High/Commercial Temperature Rated @ 45°F														
Recip	AE4425Z-AA1A	AE1166E-212-J7	2800	5/16	1/4	—	—	—	—	—	High	1/5	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE3425A-AA1A	AE1253E-212-J7	2500	5/16	1/4	—	—	—	—	—	Low	1/4	R-12	115V ~ 60Hz
Recip	AE3425Y-AA1A	AE1004E-212-J7	2800	5/16	1/4	—	—	—	—	—	Low	1/4	R-134a/R-513A	115V ~ 60Hz
Recip	AE3425Y-AA1A	AE1198E-215-J7	2800	3/8 FLARE	1/4	—	—	—	—	—	Low	1/4	R-134a/R-513A	115V ~ 60Hz
Recip	AE4430A-AA1A	AE1251E-212-J7	3000	5/16	1/4	—	—	—	—	—	High	1/4	R-12	115V ~ 60Hz
Recip	AE4430A-AA1A	AE1254E-215-J7	3000	3/8 FLARE	1/4	—	—	—	—	—	High	1/4	R-12	115V ~ 60Hz
Recip	AE4430Y-AA1A	AE1023E-212-J7	3400	5/16	1/4	—	—	—	—	—	High	1/4	R-134a/R-513A	115V ~ 60Hz
Recip	AE3430Y-AA1A	AE1153E-212-J7	3400	5/16	1/4	—	—	—	—	—	Low	1/4	R-134a/R-513A	115V ~ 60Hz
Recip	AE4430Y-AA1A	AE1199E-215-J7	3400	3/8 FLARE	1/4	—	—	—	—	—	High	1/4	R-134a/R-513A	115V ~ 60Hz
Recip	AE4430Z-AA1A	AE1167E-212-J7	3450	5/16	1/4	—	—	—	—	—	High	1/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE4430E-DS1A	AE1320E-212-J7	3200	5/16	1/4	—	—	—	—	—	High	1/3	R-22	115-127V ~ 60Hz
Recip	AE4440E-DS1A	AE1483E-209-J7	4000	5/16	1/4	—	—	—	—	—	High	1/3	R-22	115-127V ~ 60Hz
Recip	AE4440A-AA1A	AE1250E-212-J7	4000	5/16	1/4	—	—	—	—	—	High	1/3	R-12	115V ~ 60Hz
Recip	AE4440A-AA1A	AE1252E-215-J7	4000	3/8 FLARE	1/4	—	—	—	—	—	High	1/3	R-12	115V ~ 60Hz
Recip	AE4440Y-AA1A	AE1022E-212-J7	4350	5/16	1/4	—	—	—	—	—	High	1/3	R-134a/R-513A	115V ~ 60Hz
Recip	AE3440Y-AA1A	AE1155E-212-J7	4350	5/16	1/4	—	—	—	—	—	Low	1/3	R-134a/R-513A	115V ~ 60Hz
Recip	AE4440Y-AA1A	AE1200E-215-J7	4350	3/8 FLARE	1/4	—	—	—	—	—	High	1/3	R-134a/R-513A	115V ~ 60Hz
Recip	AE4440Z-AA1A	AE1168E-209-J7	4350	5/16	1/4	—	—	—	—	—	High	1/3	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE4440Y-XN1A	AE1204E-209-J7	4350	5/16	1/4	—	—	—	—	—	High	1/3	R-134a/R-513A	208-230V ~ 60Hz
Recip	AE4450E-DS1B	AE1363E-209-J7	5100	5/16	1/4	—	—	—	—	—	High	1/2	R-22	115-127V ~ 60Hz
Recip	AE4450Y-AA1A	AE1154E-209-J7	5450	5/16	1/4	—	—	—	—	—	High	1/2	R-134a/R-513A	115V ~ 60Hz
Recip	AE4450Y-AA1A	AE1395E-220-J7	5450	3/8 FLARE	1/4	—	—	—	—	—	High	1/2	R-134a/R-513A	115V ~ 60Hz

COMPRESSOR QUICK SELECT GUIDE

HIGH/COMMERCIAL TEMPERATURE RATED @ 45°F
& LOW TEMPERATURE RATED @ -10°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
High/Commercial Temperature Rated @ 45°F														
Recip	AE4456E-DS1B	AE1364E-214-J7	5800	3/8	1/4	—	—	—	—	—	High	1/2	R-22	115-127V ~ 60Hz
Recip	AE4450Z-AA1A	AE1164E-209-J7	5800	5/16	1/4	—	—	—	—	—	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip*	AE4450Z-AA3C	AE1797E-677-J7	5850	3/8	1/4	—	—	—	—	—	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE4456Y-AA1C	AE1165E-214-J7	5950	3/8	1/4	—	—	—	—	—	High	1/2	R-134a/R-513A	115V ~ 60Hz
Recip	AE4460Y-AA3C	AE1183E-677-J7	6350	3/8	1/4	—	—	—	—	—	High	1/2	R-134a/R-513A	115V ~ 60Hz
Recip	AE4460U-AA1C	AE1432E-209-J7	6900	3/8	1/4	—	—	—	—	—	High	1/2	R-290	115V ~ 60Hz
Recip	AE4470Z-AA3C	AE1184E-677-J7	8000	3/8	1/4	—	—	—	—	—	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip*	AK4510Z-NA3C	AK4ZA1ET107J70	10073	3/8	1/4	AK4510Z-NA3C	AK4ZA1ER107J70	10073	3/8	1/4	High	3/4	R-404A/R-448A/ R-449A/R-452A	208-230V ~ 60Hz
Recip*	AK4513Z-NA3C	AK4ZC1ET107J70	13071	3/8	1/4	AK4513Z-NA3C	AK4ZC1ER107J70	13071	3/8	1/4	High	1	R-404A/R-448A/ R-449A/R-452A	208-230V ~ 60Hz
Low Temperature Rated @ -10°F														
Recip	AZA1332YXA	AZ420AR-235-J7	330	1/4	3/16	—	—	—	—	—	Low	1/8	R-134a	115V ~ 60Hz
Recip	THA1358YXA	TH130AR-340-J7HV	610	5/16	1/4	—	—	—	—	—	Low	1/5	R-134a	115V ~ 60Hz
Recip	AE1390Y-AA1A	AE1191E-106-J7	870	5/16	1/4	—	—	—	—	—	Low	1/5	R-134a/R-513A	115V ~ 60Hz
Recip	TA1375Y-DS3F	TA-1298-E	745	5/16	1/4	—	—	—	—	—	Low	1/4	R-134a	115-127V ~ 60Hz
Recip	TA1380Y-DS2E	TA-1299-E	820	5/16	1/4	—	—	—	—	—	Low	1/4	R-134a	115-127V ~ 60Hz
Recip	AE2410Y-AA1A	AE1156E-679-J7	950	5/16	1/4	—	—	—	—	—	High	1/4	R-134a/R-513A	115V ~ 60Hz
Recip	AE2410A-AA1A	AE1249E-679-J7	1000	5/16	1/4	—	—	—	—	—	High	1/4	R-12	115V ~ 60Hz
Recip	AE2410Z-AA1A	AE1126E-106-J7	1050	5/16	1/4	—	—	—	—	—	High	1/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE2413A-AA1B	AE1255E-679-J7	1300	5/16	1/4	—	—	—	—	—	High	1/3	R-12	115V ~ 60Hz
Recip	AE2413A-AA1B	AE1317E-219-J7	1300	3/8 FLARE	1/4	—	—	—	—	—	High	1/3	R-12	115V ~ 60Hz
Recip	AE2413Y-AA1B	AE1240E-679-J7	1300	5/16	1/4	—	—	—	—	—	High	1/3	R-134a/R-513A	115V ~ 60Hz
Recip	AE2415Z-AA1A	AE1157E-679-J7	1600	5/16	1/4	—	—	—	—	—	High	1/3	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AJA2419ZXA	AJ303AT-336-J7	1865	3/4 Rotolock	5/16	AJ2419Z-XA1A	AJ2ZA1AF640J70	1875	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AJA2419ZXA	AJ303AT-434-J7	1865	3/8	1/4	AJ2419Z-XA1A	AJ2ZA1AF640J70	1875	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE2420Z-DS1B	AE1322E-679-J7	2050	5/16	1/4	—	—	—	—	—	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115-127V ~ 60Hz
Recip	AJA2425AXA	AJ601AT-336-J7	2450	3/4 Rotolock	5/16	AJ2425A-XA1A	AJ2AM1AF643J70	2200	1/2	5/16	High	1/2	R-12	115V ~ 60Hz
Recip	AJA2425ZXA	AJ532AT-124-B4Y	2450	1/2	5/16	AJ2425Z-XA3A	AJ2ZH1AF643A41	2389	1/2	5/16	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AJA2425ZXA	AJ532AT-336-J7	2450	3/4 Rotolock	5/16	AJ2425Z-XA3A	AJ2ZH1AF643J70	2389	1/2	5/16	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AKA2425ZXA	AK176AT-037-J7	2500	3/8	1/4	AKA2425ZXA	AK176AR-B37-J7	2500	3/8	1/4	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AE2425Z-AA3C	AE1182E-208-J7	2650	5/16	1/4	—	—	—	—	—	High	1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz

*Replacement compressor used on Tecumseh ARGUS Condensing Unit

COMPRESSOR QUICK SELECT GUIDE

LOW TEMPERATURE RATED @ -10°F



Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
Low Temperature Rated @ -10°F														
Recip*	AK2430Z-NA3C	AK2ZB3DT106J70	2989	3/8	1/4	AK2430Z-NA3C	AK2ZB3DR106J70	2989	3/8	1/4	High	3/4	R-452A/R-404A	208-230V ~ 60Hz
Recip	AJB2433ZXD	AJ604EF-436-J7	3330	3/8	5/16	AJ2433Z-XD3A	AJ2ZM1DF643J70	3724	1/2	5/16	High	3/4	R-404A	208-230V ~ 60Hz
Recip	AJB2433ZXA	AJ604AF-436-J7	3410	3/8	5/16	AJ2433Z-XA3A	AJ2ZM1AF643J70	3667	1/2	5/16	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AJB2433ZXA	AJ604AF-442-J7	3410	3/8	5/16	AJ2433Z-XA3A	AJ2ZM1AF643J70	3667	1/2	5/16	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip	AJB2433ZXA	AJ604AF-443-J7	3410	3/8	5/16	AJ2433Z-XA3A	AJ2ZM1AF643J70	3667	1/2	5/16	High	3/4	R-404A/R-407A/ R-448A/R-449A/R-452A	115V ~ 60Hz
Recip*	AK2436Z-NA3C	AK2ZC1DT107J70	3737	3/8	1/4	AK2436Z-NA3C	AK2ZC1DR107J70	3737	3/8	1/4	High	3/4	R-452A/R-404A	208-230V ~ 60Hz
Recip	AWA2440ZXD	AW610ET-111-J7	3775	1-1/4 Rotolock	3/8	AWA2440ZXD	AW610EH-111-J7	3775	1-1/4 Rotolock	3/8	High	1	R-404A	208-230V ~ 60Hz
Recip	AJB2444ZXD	AJ605EF-436-J7	4440	3/8	5/16	AJ2444Z-XD3A	AJ2ZR1DF646J70	4445	1/2	3/8	High	1	R-404A/R-449A	208-230V ~ 60Hz
Recip	AJB2444ZXD	AJ605EF-442-J7	4440	3/8	5/16	AJ2444Z-XD3A	AJ2ZR1DF646J70	4445	1/2	3/8	High	1	R-404A/R-449A	208-230V ~ 60Hz
Recip	AWA2450ZXD	AW615ET-111-J7	4600	1-1/4 Rotolock	3/8	AWA2450ZXD	AW615EH-111-J7	4600	1-1/4 Rotolock	3/8	High	1	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip*	AWA2450ZXD	AW615ET-172-J7	4600	5/8	3/8	AWA2450ZXD	AW615EH-172-J7	4600	5/8	3/8	High	1	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip*	AWA2450ZXT	AW615RT-174-J7	4800	5/8	3/8	—	—	—	—	—	High	1	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~60Hz
Recip*	AK2448Z-NA3C	AK2ZD1DT107J70	4892	3/8	1/4	AK2448Z-NA3C	AK2ZD1DR107J70	4892	3/8	1/4	High	1	R-452A/R-404A	208-230V ~ 60Hz
Recip	AWA2460ZXT	AW613RT-120-J7	6000	5/8	3/8	AWA2460ZXT	AW613RH-120-J7	6000	5/8	3/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~60Hz
Recip	AWA2460ZXT	AW613RT-121-J7	6000	1-1/4 Rotolock	3/8	AWA2460ZXT	AW613RH-121-J7	6000	1-1/4 Rotolock	3/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~60Hz
Recip	AWA2460ZXT	AW613RT-163-J7	6000	7/8	7/8	AWA2460ZXT	AW613RH-163-J7	6000	7/8	7/8	High	1-1/2	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~60Hz
Recip	AWA2460ZXD	AW613ET-099-J7	6300	5/8	3/8	AWA2460ZXD	AW613EH-099-J7	6300	5/8	3/8	High	1-1/2	R-404A	208-230V ~ 60Hz
Recip	AWA2460ZXD	AW613ET-111-J7	6300	1-1/4 Rotolock	3/8	AWA2460ZXD	AW613EH-111-J7	6300	1-1/4 Rotolock	3/8	High	1-1/2	R-404A	208-230V ~ 60Hz
Recip*	AWA2480ZXT	AW618RT-174-J7	7600	5/8	3/8	AWA2480ZXT	AW618RH-174-J7	7600	5/8	3/8	High	2	R-404A/R-407A/ R-448A/R-449A/R-452A	200-230V 3~60Hz
Recip*	AWA2480ZXT	AW618FT-172-J7	7600	5/8	3/8	AWA2480ZXT	AW618FH-172-J7	7600	5/8	3/8	High	2	R-404A/R-407A/ R-448A/R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VS2480Z-NA9A	VS2ZA1DC200J70	7630	7/8	1/2	—	—	—	—	—	High	2	R-404A/R-448A/ R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VS2480Z-FA1A	VS2ZA1RC200J70	8000	7/8	1/2	—	—	—	—	—	High	2	R-404A/R-448A/ R-449A/R-452A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV182RT-012-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195RT-037-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7	9100	7/8	1/2	AWS2512ZKZ	AW459SH-419-J7	10200	7/8	1/2	High	2	R-404A	200-230V 3~60Hz
Recip	AWA2490ZXT	AV195ET-001-J7												

COMPRESSOR QUICK SELECT GUIDE



LOW TEMPERATURE RATED @ -10°F, LOW TEMPERATURE RATED @ -10°F / MEDIUM TEMPERATURE RATED @ 20°F & MEDIUM TEMPERATURE RATED @ 20°F

Type	Legacy Model	Legacy Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Transition Model	Transition Item Number	Capacity (Btu/H)	Suction (inches)	Discharge (inches)	Motor Start Torque	Horse Power	Refrigerant	Voltage 60
Low Temperature Rated @ -10°F														
Recip*	AWA2510ZFA	AW621RT-174-J7	9000	5/8	3/8	AWA2510ZFA	AW621RH-174-J7	9000	5/8	3/8	High	2-1/2	R-404A/R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Scroll*	VS2511Z-NA9A	VS2ZC1DC200J70	10400	7/8	1/2	—	—	—	—	—	High	3	R-404A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VS2511Z-FA1A	VS2ZC1RC200J70	10500	7/8	1/2	—	—	—	—	—	High	3	R-404A/R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Recip	AVA2512ZXT	AV180RT-012-J7	12000	7/8	1/2	VS2513Z-FA1A	VS2ZD1RC200J70	13000	7/8	1/2	High	3	R-404A/R-407A/R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Recip	AVA2512ZSN	AV180ET-001-J7	12500	7/8	1/2	VS2513Z-NA9A	VS2ZD1DC200J70	12800	7/8	1/2	High	3	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AVA2512ZSN	AV180ET-041-B4Y	12500	7/8	1/2	VS2513Z-NA9A	VS2ZD1DC200A40	12800	7/8	1/2	High	3	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VS2513Z-NA9A	VS2ZD1DC200J70	12800	7/8	1/2	—	—	—	—	—	High	3	R-404A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VS2513Z-FA1A	VS2ZD1RC200J70	13000	7/8	1/2	—	—	—	—	—	High	3	R-404A/R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Scroll*	VS2519Z-NA9A	VS2ZF1DC201J70	18400	7/8	1/2	—	—	—	—	—	High	5	R-404A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Scroll*	VS2519Z-FA1A	VS2ZF1RC200J70	18400	7/8	1/2	—	—	—	—	—	High	5	R-404A/R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Scroll*	VS2522Z-FA1A	VS2ZG1RC201J70	21800	7/8	1/2	—	—	—	—	—	High	5-1/2	R-404A/R-448A/R-449A/R-452A	200-230V 3~ 60Hz
Low Temperature Rated @ -10°F / Medium Temperature Rated @ 20°F														
Recip	TCW330U-DS8B	TC1029E-038-J7	300/600	5/16	1/4	—	—	—	—	—	Low	1/13	R-290	115-127V ~ 60Hz
Recip	TCW350U-DS6B	TC1033E-038-J7	500/1000	5/16	1/4	—	—	—	—	—	Low	1/6	R-290	115-127V ~ 60Hz
Recip	TCW360U-LS6A	TC1032E-038-J7	600/1200	5/16	1/4	—	—	—	—	—	Low	1/5	R-290	115V ~ 60Hz
Recip	TCW380U-DS6B	TC1034E-038-J7	800/1640	5/16	1/4	—	—	—	—	—	Low	1/4	R-290	115-127V ~ 60Hz
Recip	TCW410Y-DS8E	TC-1155-E	1060/2060	5/16	1/4	—	—	—	—	—	Low	1/3	R-134a	115-127V ~ 60Hz
Recip	TCW410U-DS6B	TC1036E-038-J7	1150/2300	5/16	1/4	—	—	—	—	—	Low	1/3	R-290	115-127V ~ 60Hz
Recip	TCW413Y-DS8E	TC-1156-E	1150/2770	5/16	1/4	—	—	—	—	—	Low	1/3	R-134a	115-127V ~ 60Hz
Recip	TCX413U-DS1B	TC1037E-038-J7	1310/2700	5/16	1/4	—	—	—	—	—	High	1/3	R-290	115-127V ~ 60Hz
Recip	TCX415U-DS1B	TC1038E-038-J7	1470/2940	5/16	1/4	—	—	—	—	—	High	1/2	R-290	115-127V ~ 60Hz
Recip	AEX419U-DS1B	AE1528E-679-J7	1770/3540	5/16	1/4	—	—	—	—	—	High	1/2	R-290	115-127V ~ 60Hz
Recip	AEX428U-DS3C	AE1677E-677-J7	2550/5100	3/8	1/4	—	—	—	—	—	High	3/4	R-290	115-127V ~ 60Hz
Medium Temperature Rated @ 20°F														
Recip	AJA7461YXA	AJ250AT-188-J7	6110	1 Rotolock	5/16	AJ7461Y-XA3A	AJ7YP1AF643J70	6080	1/2	5/16	High	3/4	R-134a/R-513A	115V ~ 60Hz
Recip*	AJA7490ZXD	AJ779ET-444-J7	8850	1/2	3/8	AJ7490Z-XD3A	AJ7ZN1DF646J71	8195	1/2	3/8	High	1	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AJA7494ZXD	AJ202ET-188-J7	9350	1 Rotolock	5/16	AJ7494Z-XD3A	AJ7ZP1DF646J70	9653	1/2	3/8	High	1	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AJA7494ZXD	AJ202ET-206-J7	9350	1/2	5/16	AJ7494Z-XD3A	AJ7ZP1DF646J70	9653	1/2	3/8	High	1	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AJA7494ZXD	AJ202ET-435-J7	9350	3/8	3/8	AJ7494Z-XD3A	AJ7ZP1DF646J70	9653	1/2	3/8	High	1	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AWA7512ZXD	AW611ET-111-J7	11600	1-1/4 Rotolock	3/8	AWA7512ZXD	AW611EH-111-J7	11600	1-1/4 Rotolock	3/8	High	1	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz
Recip	AWA7515ZXD	AW612ET-111-J7	15400	1-1/4 Rotolock	3/8	AWA7515ZXD	AW612EH-111-J7	15400	1-1/4 Rotolock	3/8	High	2	R-404A/R-407A/R-448A/R-449A/R-452A	208-230V ~ 60Hz

*Replacement compressor used on Tecumseh ARGUS Condensing Unit

DISCONTINUED COMPRESSORS



Tecumseh is optimizing our wholesale compressor portfolio. This includes releasing new models along with rationalizing some of our current compressor lineup. Below are models and item numbers that have been discontinued as of Fall 2020.

Product Family	Legacy Model	Legacy Item Number	Status
AG Compressor	AGA4534AXN	AG155ET-017-J7	Discontinued
AG Compressor	AGA4534AXT	AG155RT-017-J7	Discontinued
AG Compressor	AGA4543AXN	AG166ET-017-J7	Discontinued
AG Compressor	AGA4543AXT	AG166RT-017-J7	Discontinued
AG Compressor	AGA5549CXT	AG122ST-003-J7	Discontinued
AG Compressor	AGA5553EXH	AG122VT-004-J7	Discontinued
AG Compressor	AGA5561EXH	AG133VT-003-J7	Discontinued
AG Compressor	AGA5563CXG	AG145TT-001-J7	Discontinued
AG Compressor	AGA5568EXN	AG144ET-002-J7	Discontinued
AG Compressor	AGA5573EXT	AG188RT-001-J7	Discontinued
AG Compressor	AGA9530ZXN	AG133FT-001-J7	Discontinued
AG Compressor	AGA9530ZXT	AG133ST-003-J7	Discontinued
AG Compressor	AGA9534ZXN	AG144FT-002-J7	Discontinued
AG Compressor	AGB5568EXH	AG144XT-003-J7	Discontinued
AJ Compressor	AJA2416AXA	AJ312AT-141-J7	Discontinued
AJ Compressor	AJA2419YXA	AJ135AT-336-J7	Discontinued
AJ Compressor	AJA2419ZXD	AJ303ET-336-J7	Discontinued
AJ Compressor	AJA2425AXD	AJ601FT-336-J7	Discontinued
AJ Compressor	AJA2425ZXD	AJ532ET-336-J7	Discontinued
AJ Compressor	AJA4461AXD	AJ311FT-141-J7	Discontinued
AJ Compressor	AJA5517EXD	AJ210FT-206-J7	Discontinued
AJ Compressor	AJA5518EXD	AJ200FT-206-J7	Discontinued
AJ Compressor	AJA5518EXV	AJ200JB-206-J7	Discontinued
AJ Compressor	AJA7441AXA	AJ530AT-336-J7	Discontinued
AJ Compressor	AJA7441AXD	AJ530FT-336-J7	Discontinued
AJ Compressor	AJA7461YXD	AJ250GT-188-J7	Discontinued
AJ Compressor	AJA7461YXD	AJ250GT-435-J7	Discontinued
AJ Compressor	AJA7465AXA	AJ201AT-188-J7	Discontinued
AJ Compressor	AJA7465AXA	AJ201AT-426-J7	Discontinued
AJ Compressor	AJA7465AXA	AJ201AT-435-J7	Discontinued
AJ Compressor	AJB5515EXD	AJ600FT-205-J7	Discontinued
AJ Compressor	AJB5515EXV	AJ600JB-205-J7	Discontinued
AJ Compressor	AJB7465AXD	AJ201GT-188-J7	Discontinued
AJ Compressor	AJB7465AXD	AJ201GT-435-J7	Discontinued
AK Compressor	AKA5470EXA	AK120AT-004-J7	Discontinued
AK Compressor	AKA5483EXA	AK130AT-004-J7	Discontinued
AK Compressor	AKA5511EXA	AK110AT-004-J7	Discontinued
AK Compressor	AKA9451ZXD	AK170ET-035-J7	Discontinued
AV Compressor	AVA4542EXN	AV144FT-001-J7	Discontinued
AV Compressor	AVA5532EXN	AV113ET-026-J7	Discontinued
AV Compressor	AVA5532EXT	AV114RT-027-J7	Discontinued
AV Compressor	AVA5535EXN	AV122ET-029-J7	Discontinued
AV Compressor	AVA5535EXT	AV123RT-027-J7	Discontinued
AV Compressor	AVA5538EXG	AV134TT-036-J7	Discontinued
AV Compressor	AVA5538EXN	AV133ET-030-J7	Discontinued
AV Compressor	AVA5538EXT	AV134RT-035-J7	Discontinued
AV Compressor	AVA5542EXG	AV145TT-036-J7	Discontinued
AV Compressor	AVA5542EXN	AV144ET-034-J7	Discontinued
AV Compressor	AVA5542EXN	AV144ET-001-J7	Discontinued
AV Compressor	AVA5542EXT	AV145RT-035-J7	Discontinued
AV Compressor	AVA5542EXT	AV145RT-001-J7	Discontinued
AV Compressor	AVA5542WNA	AV203FT-001-J7	Discontinued
AV Compressor	AVA5542WNG	AV203UT-013-J7	Discontinued
AV Compressor	AVA5542WXT	AV146RT-001-J7	Discontinued
AV Compressor	AVA5546EXG	AV169TT-036-J7	Discontinued

Product Family	Legacy Model	Legacy Item Number	Status
AV Compressor	AVA5546EXN	AV168ET-041-J7	Discontinued
AV Compressor	AVA5546EXN	AV168ET-001-J7	Discontinued
AV Compressor	AVA5546EXT	AV169RT-035-J7	Discontinued
AV Compressor	AVA5546EXT	AV169RT-001-J7	Discontinued
AV Compressor	AVA9519ZXG	AV201TT-013-J7	Discontinued
AV Compressor	AVA9519ZXN	AV200ET-003-J7	Discontinued
AV Compressor	AVA9519ZXT	AV201RT-012-J7	Discontinued
AV Compressor	AVA9522ZXT	AV203RT-001-J7	Discontinued
AV Compressor	AVB5535EXN	AV125ET-041-J7	Discontinued
AV Compressor	AVB5535EXT	AV125RT-041-J7	Discontinued
AV Compressor	AVB5542EXG	AV147TT-043-J7	Discontinued
AV Compressor	AVB5542EXT	AV147RT-041-J7	Discontinued
AV Compressor	AVB5549EXG	AV178TT-043-J7	Discontinued
AV Compressor	AVB5549EXH	AV178VT-043-J7	Discontinued
AV Compressor	AVB5549EXN	AV178ET-041-J7	Discontinued
AV Compressor	AVB5549EXT	AV178RT-041-J7	Discontinued
AV Compressor	AVB5558EXG	AV190TT-045-J7	Discontinued
AV Compressor	AVB5558EXH	AV190VT-045-J7	Discontinued
AV Compressor	AVB5558EXN	AV190ET-047-J7	Discontinued
AV Compressor	AVB5558EXT	AV190RT-045-J7	Discontinued
AV Compressor	AVA2512ZXG	AV180TT-013-J7	Discontinued
AV Compressor	AVA7524ZXN	AV179ET-001-J7	Discontinued
AV Compressor	AVA7524ZXT	AV179RT-012-J7	Discontinued
AV Compressor	AVA9522ZXN	AV203ET-001-J7	Discontinued
AV Compressor	AVA9528ZXN	AV204ET-066-J7	Discontinued
AV Compressor	AVA9528ZXT	AV204RT-001-J7	Discontinued
AW Compressor	AWA2440ZXT	AW610RT-121-J7	Discontinued
AW Compressor	AWA7512ZXT	AW611RT-121-J7	Discontinued
AW Compressor	AWA7515ZXT	AW612RT-121-J7	Discontinued
AW Compressor	AWA9490ZXN	AW616ET-111-J7	Discontinued
AW Compressor	AWA9490ZXN	AW616ET-099-J7	Discontinued
AW Compressor	AWA9490ZXN	AW616ET-163-J7	Discontinued
AW Compressor	AWA9490ZXT	AW616RT-120-J7	Discontinued
AW Compressor	AWA9490ZXT	AW616RT-121-J7	Discontinued
AW Compressor	AWA9514ZXN	AW617ET-099-J7	Discontinued
AW Compressor	AWA9514ZXT	AW617RT-120-J7	Discontinued
AW Compressor	AWF5516EXN	AW500ET-089-J7	Discontinued
AW Compressor	AWF5524EXG	AW505TT-090-J7	Discontinued
AW Compressor	AWF5524EXT	AW505RT-098-J7	Discontinued
AW Compressor	AWF5530EXG	AW508TT-090-J7	Discontinued
AW Compressor	AWF5530EXT	AW508RT-098-J7	Discontinued
AW Compressor	AWF5532EXT	AW509RT-098-J7	Discontinued
AW Compressor	AWG4520EXG	AW703UT-124-J7	Discontinued
AW Compressor	AWG4524EXG	AW705UT-124-J7	Discontinued
AW Compressor	AWG4530EXN	AW707FT-099-J7	Discontinued
AW Compressor	AWG5515EXN	AW700ET-111-J7	Discontinued
AW Compressor	AWG5515EXN	AW700ET-129-J7	Discontinued
AW Compressor	AWG5515EXT	AW700RT-121-J7	Discontinued
AW Compressor	AWG5517EXN	AW701ET-093-J7	Discontinued
AW Compressor	AWG5520EXT	AW703RT-121-J7	Discontinued
AW Compressor	AWG5520EXT	AW703RT-120-J7	Discontinued
AW Compressor	AWG5524EXT	AW705RT-120-J7	Discontinued
AW Compressor	AWG5530EXT	AW707RT-120-J7	Discontinued
AW Compressor	AWG5532EXN	AW708ET-093-J7	Discontinued



Tecumseh

TECUMSEH COMPRESSOR COMPANY LLC

Subsidiary of Tecumseh Products Company LLC

5683 Hines Drive | Ann Arbor, MI 48108

Email: technical.service@tecumseh.com

734.585.9500 | www.tecumseh.com

